

# MIDLAND®

## Model 75-785 7-Watt/40 Channel Portable CB Radio



**Y**ou can always depend on Midland's model 75-785... With its high performance, long hours of use and longer range you can keep track of family and friends. 75-785 is ideal for camping, fishing, hunting, or any outdoor activity and it's easy to carry and use.

This 40 channel portable CB radio provides great performance with 7 watts input and the FCC maximum allowable 4 watts output power (switchable to low power). A precision PLL frequency control system delivers pinpoint channel tuning every time, and an electronic microphone comes through with plenty of crisp, clear talk power.

The Hi/Low power switch changes output power to 1 watt, resulting in significantly longer battery life. Power is provided by 9 (optional) "AA" alkaline or rechargeable batteries - or your vehicle's 12V DC electrical system via the detachable power cord with its lighter plug. There are also jacks for an antenna, speaker/microphone, and battery charging.

Midland's Model 75-785 CB radio is a compact and economical way to communicate almost anywhere.

***Built to take it!***

**MIDLAND®**  
CONSUMER RADIO

1670 N. Topping Ave., Kansas City, MO 64120 [www.midlandradio.com](http://www.midlandradio.com)

# FEATURES - BENEFITS - SPECIFICATIONS

## Features and Benefits

- 33% smaller than previous model (75-784)  
Easy to carry and use
- Full 40-channel PLL operation  
Pinpoint channel tuning accuracy
- Bright LED channel display  
Easy to read
- High/low power switch  
Reduces power consumption for short-range usage. Prolongs battery life
- Battery low indicator light  
Visually warns you when batteries need replacement or charging
- Automatic noise control  
Provides noise reduction under any condition
- Push button up/down channel selection  
Fast, convenient channel changing
- Built-in electrostat electronic microphone  
Delivers clear, crisp talk power
- External power jack  
Transceiver can be powered from DC sources (cars, truck, RVs, or boats)
- Charge jack  
Nickel cadmium batteries can be charged without removing them from the radio (charger and batteries sold separately)
- Accessory jacks  
Increases radio's versatility by making it possible to use with an external antenna, speaker-mic, headphone/mic (each sold separately)
- Powered by 9 "AA" alkaline or rechargeable NiCad batteries (not included) or any 12V DC Vehicle cigarette lighter



## Model 75-785 7-Watt/40 Channel Portable CB Transceiver

## Specifications

Size: 7" H x 2½" W x 1¾" D

Frequency control: PLL

Power: 7 watts input, 4 watts output

Sensitivity: Less than 1 mV for 10 dB (S+N)/N

Controls: Variable/On/Off, Squelch/Range, High/Low power, display on, Up/Down channel

Jacks: antenna, speaker-microphone, DC power and in-unit battery charging

Accessories included: Flexible rubber antenna w/BNC connector, 12V DC vehicle power cord w/lighter socket plug and User's manual. ("AA" batteries not included)

**MIDLAND**  
CONSUMER RADIO

1670 N. Topping Ave., Kansas City, MO 64120

Phone (816) 241-8500

Fax (816) 241-5713

E-mail: [midlndcb@fss.net](mailto:midlndcb@fss.net)

[www.midlandradio.com](http://www.midlandradio.com)